



TREND NETWORKS

NavITeK IE

Upgrade Information



NavITEK IE Software Release Notes

Version 1.0.76 – October 2023

- Updated LCD touchscreen driver to prevent false activations.
- Checks storage memory for bad areas to reduce likelihood of boot errors.

Version 1.0.68 – January 2021

- Added Japanese language support.
- Added TP Link wireless dongle (TL-WN725N Ver:3.0) support for IDEAL AnyWARE
- Added built-in LLDP, SNMP packets capture and replay function to avoid external PC and hub required for debugging Discovery port info and SNMP/PROFINET request & response messages.
- Blanks Pages in PDF Report when SNMP requests failed to receive response

NaviTEK IE Software Update Procedure

Update for testers with serial numbers starting with 151 (NaviTEK IE)



This update is not reversible to previous versions.

All saved data will be erased during the update. Ensure all saved data is backed up before updating the software.

1. Obtain a USB flash drive formatted to FAT or FAT32, NTFS formatted drives are not compatible. The maximum supported USB drive size is 16GB.
2. Copy the “NaviTEK-IE-md5.bin” upgrade file from your computer to the root of the flash drive.
3. Ensure that the tester is connected to the mains power supply or that the battery is fully charged.
4. Power on the tester and insert the flash drive.
5. Save the tester configuration to the flash drive. Select SETUP / SYSTEM / CONFIG / SAVE.
6. Save stored test results to the flash drive. Select JOBS / OPTIONS / ALL TO USB.
7. Update the system software. Select SETUP / SYSTEM / UPDATE.
8. Confirm the process by selecting UPDATE to begin.
9. Wait for the update to complete and the tester to restart. Select your language after restart.
10. Confirm the new software version by selecting SETUP / SYSTEM / ABOUT.
11. Load the previously saved tester configuration. Select SETUP / SYSTEM / CONFIG / LOAD.
12. Check the date and time settings. Select SETUP / SYSTEM / TIME.
13. The tester is now ready to use.